



Digital Power Amplifier

T-61000D



Specifications

Model	T-61000D
Rated Power Output	1000W
Speaker Outputs	70V, 100V & 4~16Ω
Input Sensitivity & Impedance	775mV/10KΩ, Unbalanced XLR/TRS Input
Output Sensitivity & Impedance	775mV/470Ω, Unbalanced XLR/TRS output
Frequency Response	80Hz~16KHz (+1dB, -3dB)
S/N Ratio	>90dB
THD	Less than 0.5% at 1KHz, 1/3 rated power
Cooling	Fan automatically start up when temp reaches 45°C
Protection	Over heat, over load, short circuit
Power Supply	220V/50Hz
Power Consumption	1300W
Net Weight	8.6Kg
Dimension	484x398x88mm

Description

* Class-D broadcast power amplifier is a high-performance single-channel high-power power amplifier with switching power supply. The structure is compact and reasonable. The intelligent protection circuit adopts advanced class-D digital power amplifier and soft switching power supply to ensure the stability and reliability and protect amplifiers and speakers under extreme conditions.

* It can provide regional power amplification for the system, which is suitable for broadcasting reinforent in a large area, such as medium & large schools, buildings, clubs, venue bars, parks, etc.

Features

- * The 2U streamlined black alumina brushed panel is perfectly combined with reasonable and compact interior, which is exquisite process.
- * The brand-new exclusive third-generation Class-D digital power amplifier, efficient power amplifier circuit, light weight, long system lifespan, high-fidelity sound quality, and perfectly restored sound source quality.
- * A good pipe-type heat dissipation structure and built-in automatic temperature control fan cooling system to effectively remove hot air, reduce temperature, and extend normal operation time.
- * 1-channel LINE unbalanced TRS/XLR high-quality multi-function input interface, 1-channel LINE balanced XLR cascade output.
- * Built-in PFC circuit and soft switching power supply technology. Automatic soft start enables 92% ultra-high system efficiency.
- * New power amplifier circuit to ensure zero crossover distortion and lossless signal quality during reinforent.
- * Built-in intelligent clipping distortion and over-current protection system can effectively protect the speaker unit.
- * It has multiple intelligent detection and protection systems for over temperature, over voltage, under voltage, over current and short circuit.
- * 2 output modes: constant impedance 4-16Ω and constant voltage 100V are optional.

Rear Panel

